

## ENS-EYECONNECT (For Windows)

### FEATURES

Supports face statistics in list or graphics
Supports managing up to 64 people counting cameras in one zone and displaying real-time statistics
Supports people counting statistics in list or graphics
Add device via P2P
Live view with audio and remote playback through P2P
Switch P2P server region

### SPECIFICATION

MODEL	Model No.	ENS-EYECONNECT
	Type	Video Management Software
	Supported Devices	IPC, NVR, XVR, PTZ etc.
	Max Connected	200 IP devices or 512 channels
	Device Management	Add/delete/edit user and configure user authority, Set period of validity
	System Framework	Common functions and basic functions Drag to add new function icon or remove it Drag to change function icon order
	Login	Create password when first start the software Support forgot password by protection questions Auto login, remember password Support switching languages in login interface
EYECONNECT SMART CLIENT EXPRESS	Device Management	Auto search devices within same LAN, supports batch and one-key addition Support manual addition by IP, DDNS, EasyDDNS, P2P (Only for Windows version) Support group management Support acquiring device channel name or sync channel name to devices Support jumping to device IE interfaces in default browser Support export and import of device and group organization list
	Preview	Support device list and device online status Support one-key to connect/disconnect all channels Support 1/2/3/4/1-5/1-7/9/10/13/16/17/25/36/49/64 window division mode and customization of display split Support to enable/disable audio and two-way audio Support capture and one-key to capture all channels Support to switch main and sub stream, set video parameters Support record and one-key to record all channels Support PTZ control, focus, aperture, preset, light/wiper control Support saving view, view rotating and group switch Support face capture and display body temperature info during preview Support face recognition and display comparison result
	Playback	Support device list and device online status Playback control, play/pause/fast forward/slow forward/step forward Support 1/2/3/4 window division mode Support capture and one-key to capture all channels Support to enable/disable audio Search video by calendar, date, storage location, stream type, etc. Download video clip by file or by time
	Operation Logs	Query operation logs by time, type, user, etc. Export log information

## ENS-EYECONNECT (For Windows)

### SPECIFICATION

MODEL		ENS-EYECONNECT		
	Model No.			
	Type	Video Management Software		
DATA STATISTICS	Face Statistics	Show face data statistics in list or graphics according to different filter		
	Visitor Flow Statistic	Manage up to 64 people counting camera in one zone and set configuration of people counting rule Preview of people counting camera		
		Display peak number, current number and line chart in real time Support to set time duration of people counting, people capacity alarm, rapidly increased number alarm and number of people stay Show reported statistic in list or graphics according to different filter		
SYSTEM CONFIGURATION	Common Settings	Set capture and download file path Automatic login Data backup/recover/clear up/re index (re index face capture and record) Change language and software skin English		
		Video	Set save time of log and alarm log Set stream switch by automatically or manually Set play strategy, good fluency or minimum delay Hardware decoding available for Windows version Set download format, SDV, AVI and MP4 are supported	
			Alarm Grade	Set alarm grade
			Storage Management	Set recoding package time, format, stream type Set space strategy, storage location
	Intelligent Application	Enable intelligent application to receive face capture pictures and face recognition results Set face picture save duration by day Check deletion strategy to set visitor flow statistic save duration by month		
		P2P Setting	Set P2P server region	
	ALARM	Real Time Alarm	Real time alarm in Alarm Management, quick to play alarm video or real time video Support alarm filter by alarm grade Operator can handle and input comment to real time alarm Turn on/off alarm audio of software	
History Alarm		Query history alarm by time, source, status, user Support alarm filter by alarm grade Operator can handle and input comment to history alarm		

## ENS-EYECONNECT (For Windows)

### CONNECTION PERFORMANCE

Device Type	Network	Channels Number
Norden Device	LAN	512
Norden P2P Devices	WAN	512

### EXPORT PERFORMANCE OF FACE PICTURE

Data	Windows	Mac Mini	MacBook	iMac
1 Day Per Channel	3s	<3s	<3s	<3s
1 Week Per Channel	10s	11s	7s	8s
1 Month Per Channel	48s	1'20"	19s	30s
3 Month Per Channel	30'7"	5'59"	1'27"	1'55"
91W Face Pictures	4h7min	40min	1h2min	1h19min

### RECOMMENDED SYSTEM REQUIREMENT

OS	Windows7, window10, Mac OS
CPU	i5-8Generation
Memory	4G
HDD	512G
Network Card	100/1000M Self Adaptive
GPU	GTX1050 4G
Display	1920x1080

\*\* Software specifications are subject to change without any prior notification.